

# Color Prime® Chroma – Switching Guide



Thanks for choosing **DTF Station!** This guide will help you safely replace your current CMYK inks with **Color Prime® Chroma CMYK Inks**. For additional support, send us a message in our [Discord community](#).

**Please Note:** Color Prime® Chroma is launching in CMYK only. White is still in development and will debut in mid to late 2026. We're taking the time to perfect it so it meets the same reliability and consistency you expect from DTF Station.

## INSTRUCTIONS: Switching to Chroma

### Drain Current Ink

1. **Use up current ink** – To avoid wasting ink, wait until ink levels are as low as possible to switch
2. Using a syringe, **pull remaining ink out of each tank** and dispose into waste bottle
3. **Rinse** syringe and **repeat** step 2 for all applicable ink tanks
4. Perform regular maintenance – **Clean** with a swab around the **print head, capping station, and wiper blade**

5. Run **"Fill Ink"** until ink lines are empty - [Menu] → [Head Maintain] → [Fill Ink] → [Left Head]
6. **Close valves or engage clamps** as needed to force ink drain

## Fill With Chroma

1. **Fill ink tanks with Color Prime® Chroma** after shaking thoroughly
2. Run **[Fill Ink]** - [Menu] → [Head Maintain] → [Fill Ink] → [Left Head]
3. Perform **3 head cleanings** back-to-back

## STEP-BY-STEP VIDEO: Switching to Chroma

### For Prestige R1

▼ Scan Here to Watch



<https://youtu.be/9ti5J7SwL8A>

### For All Other Prestige Models

▼ Scan Here to Watch



<https://youtu.be/33EqzjhaTLE>

## Download ICC Profiles

▼ Scan Here to Watch



<https://youtu.be/xQP9-7ZDONE>

For the latest ICC profiles, visit [color-prime.com](https://color-prime.com) or contact your preferred dealer. Scan the QR code or click the YouTube link for a step-by-step video on downloading and installing ICC profiles.